

Since 1898  
**CONSEW**®

# SERIES KP

1/2 / 3/4 / 1  
**HORSEPOWER  
CLUTCH MOTORS**

WITH  
ENERGY EFFICIENT CIRCUITRY  
PRELUBRICATED SEALED BALL BEARINGS  
BUILT-IN LIGHT RECEPTACLE  
REVERSING PLUG (single phase only)  
DUAL VOLTAGE SWITCH (single phase only)  
POWER SWITCH/LINE CORD/PLUG (single phase only)  
VIBRATION ABSORBING RUBBER MOTOR MOUNTS  
BELT PULLEY GUARD

- Open ventilated construction for low temperature - air flow directed away from operator
- Long life special compound cork friction material ensures efficient power transmission with minimal operator effort
- Thumb screw adjustment to regulate treadle pressure
- Simple brake and clutch adjustment
- 3/4" Pulley shaft
- UL Listed Motor available
- 1-phase single voltage and dual voltage complete with switch and reversing plug




## HIGH TORQUE, HEAVY DUTY 1/2 & 3/4 HORSEPOWER CLUTCH MOTORS

### AVAILABLE TYPES AND RATINGS:

Model	H.P.	Voltage	Phase	Hz.	R.P.M.
M12	1/2	220 VAC	3 Ph	60 Hz	3450
M13	1/2	220 VAC	3 Ph	60 Hz	1725
M14	1/2	110 VAC	1 Ph	60 Hz	3450
M15	1/2	110 VAC	1 Ph	60 Hz	1725
M20	1/2	110/220	1 Ph	50/60 Hz	3450
M22	1/2	110/220	1 Ph	50/60 Hz	1725
M21	1/2	220/380	3 Ph	50/60 Hz	3450
M23	1/2	220/380	3 Ph	50/60 Hz	1725
M17	3/4	110 VAC	1 Ph	60 Hz	3450
M24	3/4	110 VAC	1 Ph	60 Hz	1725
M18	3/4	220 VAC	3 Ph	60 Hz	3450
M25	3/4	220 VAC	3 Ph	60 Hz	1725
M17D	3/4	110/220	1 Ph	50/60 Hz	3450
M24D	3/4	110/220	1 Ph	50/60 Hz	1725
M18D	3/4	220/380	3 Ph	50/60 Hz	3450
M25D	3/4	220/380	3 Ph	50/60 Hz	1725

## HIGH TORQUE EXTRA HEAVY DUTY 1 FULL HORSEPOWER CLUTCH MOTORS



### AVAILABLE TYPES AND RATINGS:

Model	H.P.	Voltage	Phase	Hz.	R.P.M.
M112	1	220 VAC	3 Ph	60 Hz	3450
M113	1	220 VAC	3 Ph	60 Hz	1725
M114	1	110 VAC	1 Ph	60 Hz	3450
M115	1	110 VAC	1 Ph	60 Hz	1725

Other voltages, frequencies and horsepowers are available on special order basis

Single and three phase push-button switches and wiring for all clutch motors available from inventory.